

## Pré-Amplifier Range PR 200

Rating: Not Rated Yet

[Ask a question about this product](#)

### Description

Possible to be directly supplied at 5V by the DVB-T receiver  
Amplifiers with low noise

REF.		PR-200	PR-201
ENTRADAS INPUTS		1	1
ENTRADAS INPUTS		BIII/UHF	UHF
BANDA COBERTA BAND RANGE	MHz	170-790	470-790
GAINHO GAIN	dB	15	
NÍVEL MÁXIMO SAÍDA MAXIMUM OUTPUT LEVEL	dBuV	96*	
FACTOR DE RUÍDO NOISE FIGURE	dB	<1	
CONSUMO CONSUMPTION	mA	10	
ALIMENTAÇÃO SUPPLY	VDC	5...24V ---	
CONEXÃO CONNECTEURS CONNECTION		Fichas tipo "F" Fiches type "F" "F" Connectors Conectores tipo "F"	



Para mais informações consulte o manual de instruções disponível em www.technet.com.br  
Pour plus d'informations consultez le manuel de l'utilisateur disponible en www.technet.com.br  
Para mais informações consulte o manual de instruções disponível em www.technet.com.br